

Starter Kit I/O Expansion Board Information Sheet

The Starter Kit I/O Expansion Board provides starter kit users with full access to MCU signals, additional debug headers, and connections of PICtail™ Plus daughter boards. MCU signals are available for attaching prototype circuits or monitoring signals with logic probes. Headers are provided for connecting JTAG tools or Microchip tools using the 2-wire (ICSP™) interface.

Table 1 shows the mapping between different header interfaces on the board.

TABLE 1: HEADER INTERFACE MAPPING

J1 Pin #	J2 Pin #	J3 Pin #	J4 Pin #	J10 Pin #	J11 Pin #	J1 Pin #	J2 Pin #	J3 Pin #	J4 Pin #	J10 Pin #	J11 Pin #
1	65	65	65	1	—	67	—	—	—	30	—
3	68	68	68	4	—	68	—	—	—	—	32
4	73	73	73	—	1	69	—	—	—	32	—
5	67	67	67	3	—	70	12	12	12	—	33
6	74	74	74	—	3	71	43	43	43	33	—
7	116	116	116	5	—	72	11	11	11	—	34
8	66	66	66	—	4	73	44	44	44	34	—
9	115	115	115	6	—	74	40	40	40	—	36
10	27, 60	27, 60	27, 60	—	6	76	38	38	38	—	38
13	114	114	114	7	—	79	49	49	49	36	—
14	29, 62	29, 62	29, 62	—	5	81	50	50	50	35	—
15	113	113	113	8	—	83	17	17	17	38	—
16	30	30	30	—	8	84	6	6	6	—	35
17	112	112	112	9	—	85	18	18	18	37	—
18	28	28	28	—	7	86	8	8	8	—	37
19	111	111	111	10	—	87	—	—	—	42	—
20	105	105	105	—	10	88	2	2	2	—	41
21	110	110	110	11	—	90	4	4	4	—	43
22	106	106	106	—	9	91	3	3	3	41	—
23	109	109	109	12	—	92	20	20	20	—	45
24	99	99	99	—	12	93	5	5	5	44	—
25	98	98	98	13	—	94	19	19	19	—	47
26	100	100	100	—	11	95	7	7	7	43	—
27	104	104	104	15	—	97	1	1	1	46	—
28	97	97	97	14	—	101	79	79	79	47	—
29	103	103	103	16	—	102	—	—	—	—	52
30	89	89	89	—	14	103	80	80	80	48	—
31	90	90	90	17	—	105	81	81	81	49	—
32	—	—	—	—	13	106	52	52	52	—	42
35	85	85	85	18	—	107	82	82	82	50	—
36	—	—	—	—	16	108	51	51	51	—	44
37	86	86	86	19	—	109	—	—	—	51	—
38	—	—	—	—	15	110	34	34	34	—	46
39	87	87	87	20	—	111	—	—	—	52	—
40	96	96	96	—	18	112	36	36	36	—	48
41	88	88	88	21	—	113	45	45	45	53	—
42	95	95	95	—	17	114	—	—	—	—	51
44	94	94	94	—	20	115	46	46	46	54	—
45	35	35	35	23	—	116	—	—	—	—	53
46	93	93	93	—	19	117	—	—	—	55	—
47	37	37	37	24	—	118	72	72	72	—	54
48	—	—	—	—	21	119	—	—	—	56	—
49	39	39	39	25	—	120	71	71	71	—	56
50	—	—	—	—	24	123	—	—	—	57	—
51	33	33	33	26	—	124	70	70	70	—	58
52	—	—	—	—	23	125	—	—	—	58	—
54	102	102	102	—	26	126	69	69	69	—	60
58	101	101	101	—	25	127	83	83	83	59	—
62	—	—	—	—	29	128	—	—	—	—	55
63	77	77	77	29	—	129	84	84	84	60	—
64	14	14	14	—	30	130	78	78	78	—	57
65	—	—	—	31	—	132	—	—	—	—	59
66	13	13	13	—	31						

Americas

Atlanta - 678-957-9614
 Boston - 774-760-0087
 Chicago - 630-285-0071
 Cleveland - 216-447-0464
 Dallas - 972-818-7423
 Detroit - 248-538-2250
 Indianapolis - 317-773-8323
 Los Angeles - 949-462-9523
 Phoenix - 480-792-7200
 Santa Clara - 408-961-6444
 Toronto - 905-673-0699

Europe

Austria - Wels - 43-7242-2244-39
 Denmark - Copenhagen - 45-4450-2828
 France - Paris - 33-1-69-53-63-20
 Germany - Munich - 49-89-627-144-0
 Italy - Milan - 39-0331-742611
 Netherlands - Drunen - 31-416-690399
 Spain - Madrid - 34-91-708-08-90
 UK - Wokingham - 44-118-921-5869

Asia/Pacific

Australia - Sydney - 61-2-9868-6733
 China - Beijing - 86-10-8569-2100
 China - Chengdu - 86-28-8665-5511
 China - Chongqing - 86-23-8980-9588

Asia/Pacific (Continued)

China - Hangzhou - 86-571-2819-3187
 China - Hong Kong SAR - 852-2401-1200
 China - Nanjing - 86-25-8473-2460
 China - Qingdao - 86-532-8502-7355
 China - Shanghai - 86-21-5407-5533
 China - Shanghai - 86-21-5407-5533
 China - Shenyang - 86-24-2334-2829
 China - Shenzhen - 86-755-8203-2660
 China - Wuhan - 86-27-5980-5300
 China - Xiamen - 86-592-2388138
 China - Xian - 86-29-8833-7252
 China - Zhuhai - 86-756-3210040
 India - Bangalore - 91-80-3090-4444
 India - New Delhi - 91-11-4160-8631
 India - Pune - 91-20-2566-1512
 Japan - Osaka - 81-66-152-7160
 Japan - Yokohama - 81-45-471-6166
 Korea - Daegu - 82-53-744-4301
 Korea - Seoul - 82-2-554-7200
 Malaysia - Kuala Lumpur - 60-3-6201-9857
 Malaysia - Penang - 60-4-227-8870
 Philippines - Manila - 63-2-634-9065
 Singapore - 65-6334-8870
 Taiwan - Hsin Chu - 886-3-5778-366
 Taiwan - Kaohsiung - 886-7-536-4818
 Taiwan - Taipei - 886-2-2500-6610
 Thailand - Bangkok - 66-2-694-1351

11/29/11



MICROCHIP

Microchip Technology Inc. • 2355 West Chandler Blvd. • Chandler, AZ 85224-6199

www.microchip.com

The Microchip name and logo, the Microchip logo, and MPLAB are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries. All other trademarks mentioned herein are property of their respective companies. © 2011-2012, Microchip Technology Incorporated, Printed in the U.S.A. All Rights Reserved. 11/11

DS51950B



Schematic (Sheet 1 of 1)

